

### Smart Pet Feeder · Light 🔁

TECHNOLOGY CARES FOR PET HEALTH

# User Instructions

Before using this product, please read the instructions in this manual thoroughly.

#### Warnings:

 Please use this device indoor. Do NOT place it under direct sunlight. Please keep away from fire sources.

• Do NOT put objects or items other from pet food into the barrel in case of device error or mistaken by pet.

 Please make sure the power cord is in place and will not be trampled, tripped, bite or damaged to avoid electric shock and other emergencies.

· The device body is NOT to be washed or soaked by water.

#### Attention:

· The device is suggested to be placed at a corner or against a wall to avoid tackled by pet.

· Do NOT disassemble, modify or repair this product by your own, otherwise all warranty and service rights will be waived.


· This product is suitable for dry pet food up to 16mm in diameter.

· Do NOT put in wet food so as not to cause blocking of the outlet channel or components damages.

• Shape and density of pet food may effect the actual capacity of the barrel; The amount of grain of each serving may vary from different grain density also.

· If there is any travel arrangement, please install dry batteries into the product in advance in case any power failure at home happens when you are away.

## Product Introduction



#### **Manual Button:**

Manual feeding: Click the button two times to outlet 2 servings of grain. Device Untethering: Long press the button for 7 seconds.


#### Indicator Light:

- White flashing: network unpaired
- **2** White on: device functioning
- Sellow on: lack of grain
- 4 Red on: grain stuck or device error
- B Red flashing: battery low

# Packaging Contents

#### Note:

After opening the package, please ensure that the product is intact and compare the accessories with the diagram below to confirm their completeness. Due to ongoing product updates and iterations, some accessories may undergo adjustments. Please refer to the actual items for accuracy.





#### Connect the power adapter

Connect the power adapter to the power interface at the bottom of the device, then plug it into the socket.Once you hear a short beep, the device has been successfully powered on.

#### Download the APP

Scan the QR code on the right to download "Dipet Life" App and sign in. Then scan the QR code below to view tutorials on unboxing, installation, device networking and usages.

#### Network configuration/unbind

First-time network configuration: Open the "Dipet Life" App, place your phone near the device, and follow the network configuration process as shown in the app. Scan the QR code in the illustration for tutorials.

Device unbinding(resetting network configuration): Long-press the device's "Manual Button" for 7 seconds, listen for a short beep, and observe the indicator light flashing white, indicating successful device unbinding and network configuration reset.



#### **Manual Feed Dispensing**

• ×2 Rapidly press the device's Manual Button twice, and the device will dispense 2 servings of feed.

#### Child Lock

Activation: Enable the child lock on the device control page within the app. Once activated, the device's Manual Button will be locked.

Deactivation: After powering off the device and turning it back on, the device's Manual Button will be unlocked. Alternatively, deactivate the child lock on the device control page within the app. Once deactivated, the device's Manual Button will be unlocked.

#### **Battery Replacement**

Open the bottom battery cover and replace with four new AAA batteries.




#### **Dessicant Replacement**

• Open the desiccant box and remove the used desiccant packet.

Take a new desiccant packet and place it inside the box. Cover the box and put the top cover back in place.

It is recommended to replace the desiccant packet every 1-3 months.



#### **Pet Food Addition**


The device will automatically check if there is enough pet feed in the storage barrel. If it's insufficient, the indicator light will stay orange.

Open the top cover to add pet feed to the storage barrel.



#### Cleaning of Stainless Steel Barrel

The stainless steel barrel can be removed for wiping or washing with water. After air-drying, it can be placed back for use.



#### **Cleaning of Feed Bowl**

Due to the attachment of food residues leading to bacterial growth, we recommend cleaning the feed bowl once every 3 days. After removing the feed bowl, wipe or wash it with water, let it air-dry, and then put it back for use.

## **O** Product Specifications

Product Name: Smart Pet Feeder [Light SE] Product Model: NFSFE32A Main Material: ABS, SUS304, Porcelain Capacity: 2.8L Product Size: 340\*200\*355mm N.W.: ≈2.1kg Connect Method: Wi-Fi (2.4GHz) Input: 5V=2A Product Grade: Qualified

This product contains a wireless transmitter module with the approval code of CMIIT ID: 2020DP2713.

# Warranty Terms

Dear customers, thank you for purchasing this product, please read the below warranty terms carefully before using:

#### 12-month Warranty & Lifetime Customer Support

Only apply to eligible purchases made directly from the Pet Marvel authorized distributors. Warranty coverage applies to the original owner and the original product only. And is not transferable.

The following conditions are not covered by the warranty:

- · Any malfunction or defect caused by improper use of environment or conditions;
- Any fault or defect caused by improper installation, misuse, unauthorized maintenance, force majeure events, or other external reasons;
- · Any fault or defect caused by the use of non-original fittings or accessories;
- . The product has exceeded the warranty period;
- Other failures or damages caused by none of the product design, technology, manufacturing process, or quality problems;
- · Normal fading, wear and tear, or consumption during the use of the product;
- Not able to provide a valid purchase certificate.

### For warranty service and more information, please get in touch via Email: service@petmarvel.com



Note: Pictures on this brochure are for reference only, and the product is subject to the real object.